
NOTSTROM KIT LED DRIVER CC / CV **ALL MULTI**EMERGENZA KIT



SERIE ALVIT | B96-ALL2471K

Ausgang: CC (Konstant-Strom) / CV (Konstant-Spannung)

Uscita: CC (corrente costante) /

CV (tensione costante)

LED Notlichteinsatz

LED Illuminazione d'emergenza















EIGENSCHAFTEN | CARATTERISTICHE

| Art. Nr. | W | V in | Amp. | V out | Amp. out | Batt. | Auton. h | Dimensions | VP |
|--------------|---------|---------------|----------|--------------|---------------|-----------|----------|-----------------|----|
| | | | CC (Kor | nstant-Strom | Corrente c | ostante) | | | |
| B96-ALL2471K | 4 x 1 W | 220 - 240 VAc | / | 12 - 24 VDc | 1 x 350 mA | 7,2 - 1,6 | 8 h | 105 x 46x 24 mm | |
| | | | | | 2 x 350 mA | 7,2 - 1,6 | 6 h | | |
| | | | | | 3 x 350 mA | 7,2 - 1,6 | 4 h | | |
| | | | | | 4 x 350 mA | 7,2 - 1,6 | 3 h | | |
| | | C | V (Konst | tant-Spannur | ng Tensione | costante) | | | |
| | | | | 24 V | 50 mA | 7,2 - 1,6 | 5 h | | |
| | | | | 24 V | 75 mA | 7,2 - 1,6 | 3 h | | |
| | | | | 24 V | 150 mA | 7,2 - 1,6 | 2 h | | |

