

# AL3 DRIVER LED CC / CV



**SERIE ALVIT | B96-AL3**

**Ausgang: CC (Konstant-Strom) / CV (Konstant-Spannung)**  
**Uscita: CC (corrente costante) / CV (tensione costante)**

**LED Netzteil On / Off**  
**LED Alimentatore On / Off**



## EIGENSCHAFTEN | CARATTERISTICHE

Art. Nr.	W	V in	Amp.	V out	Amp. out	IP	ta	Dimensions	VP
<b>CC (Konstant-Strom   Corrente costante)</b>									
B96-AL335CC	5,6 W	220 - 240 VAc	/	3 - 16 VDC	350 mA	IP 20	-10 ... +50°C	68 x 31 x 21 mm	60
B96-AL350CC	6 W	220 - 240 VAc	/	3 - 11 VDC	500 mA	IP 20	-10 ... +50°C	68 x 31 x 21 mm	60
B96-AL370CC	7,7 W	220 - 240 VAc	/	3 - 11 VDC	700 mA	IP 20	-10 ... +50°C	68 x 31 x 21 mm	60
<b>CV (Konstant-Spannung   Tensione costante)</b>									
B96-AL312CV	6 W	220 - 240 VAc	/	12 VDC	0,5 A	IP 20	-10 ... +50°C	68 x 31 x 21 mm	60
B96-AL324CV	6 W	220 - 240 VAc	/	24 VDC	0,25 A	IP 20	-10 ... +50°C	68 x 31 x 21 mm	60

